



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:			
Item Number:	776615	776616	776618
Ordering Code:	LED11A21/27K/FIL/3	LED11A21/30K/FIL/3	LED11A21/27K/FIL/M/3

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Best	1	6	Dims down to 10%
		SureSlide	6633-P	Best	1	6	Dims down to 0.1%
		Vizia	VPI06-1LZ	Good	2	6	Dims down to 5%
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 2%
		Diva	DV-600	Best	1	6	Dims down to 0.1%
		SkyLark	S-600	Best	1	6	Dims down to 0.1%
		Maestro	MAW-600	Good	2	6	Dims down to 4%
	Legrand	Titan	CD703-PW	Best	1	6	Dims down to 12%
		Harmony	D703-PTC	Best	1	6	Dims down to 0.1%
		Harmony	H703-PTC	Best	1	6	Dims down to 0.1%
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 0.1%
		Sureslide	6674	Best	1	6	Dims down to 5%
		Decora	6672	Best	1	6	Dims down to 2%
	Lutron	SkyLark Countour	CTCL-153	Best	1	6	Dims down to 0.1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 0.1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 3%
		SkyLark	SCL-153P	Best	1	6	Dims down to 0.1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 0.1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 2%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 2%
		Harmony	HCL453PTC	Best	1	6	Dims down to 12%
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 25%
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Dims down to 8%
		IlumaTech	IPE04	Good	1	6	Dims down to 5%
		Decora	6615-P	Bad	1	6	Dims down to 31%
	Lutron	SkyLark Countour	CTELV-303P	Good	1	6	Dims down to 6%
		Diva	DVELV-300P	Good	1	6	Dims down to 6%
		Maestro	MAELV-600	Good	1	6	Dims down to 7%, minor flicker at LE with 1-6
		SkyLark	SELVB-300P	Good	1	6	Dims down to 6%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 8%
	Legrand	Scene Director	SECELV	Good	1	6	Dims down to 17%
	Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6
Decora			6613-P	Best	1	6	Dims down to 0.3%
Lutron		Maestro	MALV-600	Good	2	6	Dims down to 4%
		Harmony	DLV703-PW	Best	1	6	Dims down to 0.1%
Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 10%, minor flicker at LE with 1	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 12%
	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ	N/A			
	Insteon	SwitchLin Remote Control dimmer		N/A			
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 4%, minor flicker at LE with 1-6
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A			
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
	GE	Z WAVE	ZW3005	Good	1	6	Dims down to 2%, minor flicker at LE with 1-6
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 15%
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 4%
		Harmony	H703PTUTC	Good	1	6	Dims down to 19%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 0.1%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	