



## Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	PARs Dimmable & Wet Rated: PAR30					
<b>Item Number:</b>	772720	772721	772723	772724	772726	772727
<b>Ordering Code:</b>	LED13PAR30S/NF25/827/WD	LED13PAR30S/FL40/827/WD	LED13PAR30S/NF25/830/WD	LED13PAR30S/FL40/830/WD	LED13PAR30S/NF25/840/WD	LED13PAR30S/FL40/840/WD
<b>Item Number:</b>	772730	772731	772733	772734	772736	772737
<b>Ordering Code:</b>	LED13PAR30L/NF25/827/WD	LED13PAR30L/FL40/827/WD	LED13PAR30L/NF25/830/WD	LED13PAR30L/FL40/830/WD	LED13PAR30L/NF25/840/WD	LED13PAR30L/FL40/840/WD

### Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Best	1	6	
		SureSlide	6633-P	Best	1	6	
		Vizia	VPI06-1LZ	Bad	1	6	5+ minimum load without ghosting
	Lutron	Toggler	TG-600	Best	1	6	
		Diva	DV-600	Best	1	6	
		Skylark	S-600	Best	1	6	
		Maestro	MAW-600	Bad	1	6	11+ minimum load without ghosting
	Legrand	Titan	CD703-PW	Good	1	6	Minor flicker at LE with 1-4
		Titan	CDLV703-PW	Good	1	6	Shimmering at LE with 1-6
		Harmony	D703-PTC	Good	1	6	Shimmering at LE with 1-6
		Harmony	H703-PTC	Best	1	6	
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	
		Sureslide	6674	Best	1	6	
		Decora	6672	Best	1	6	
	Lutron	Diva	DVCL-153PL	Best	1	6	
		Toggler	TGCL-153PH	Best	1	6	
		Maestro	MACL-153MLH	Best	1	6	
		Skylark	CTCL-153	Best	1	6	
		Skylark	SCL-153P	Best	1	6	
		Radio RA	RA2RR-6CL-PD	Best	1	6	
	Legrand	Harmony	DCL453-PTC	Best	1	6	
Harmony		HCL453PTC	Best	1	6		
		Adorne Paddle	ADPD453LM2	Best	1	6	
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	
		IllumaTech	IPE04	Best	1	6	
		Decora	6615-P	Bad	1	6	Dims down to 45%
	Lutron	Skylark	SELVB-300P	Best	1	6	
		Skylark Countour	CTELV-303P	Best	1	6	
		Diva	DVELV-300P	Best	1	6	
		Maestro	MAELV-600	Best	1	6	
	Legrand	VIERTI	VTEL-600M-W	Best	1	6	
		Scene Director	SCELV	Good	1	6	Dims down to 30%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Bad	1	6	9+ minimum load
		Decora	6613-P	Best	1	6	
	Legrand	Maestro	MALV-600	N/C	1	6	It does not turn on with 1-6
		Harmony	DLV703-PW	Good	1	6	Shimmering at LE with 1-6
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	
		Miro Decorator	DRD4-W	Good	1	6	3+ minimum load without ghosting
		Harmony	H703PTUTC	Best	1	6	
		Adorne Whisper	ADWR700MMTUW2	Bad	1	6	Flicker at LE with 1-6
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	
		Decorator	DAL06P-C2-K-L	Best	1	6	
		Skye	SAL06P-W-K-L	Best	1	6	

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	

Contact Information:  
Bulbrite Industries Inc.  
145 West Commercial Avenue  
Moonachie, New Jersey 07074  
PHONE: 1-800-528-5555  
FAX: 1-800-441-7708  
Email: ProductSupport@bulbrite.com  
©2017 Bulbrite Industries Inc.  
All Rights Reserved.