

145 West Commercial Ave.

Dimmer Compatibility Guide

772253 772254 Item Number: Ordering Code: Item Number: LED15PAR38/B-FL40/840/WD/2 LED15PAR38/B-FL40/830/WD/2

Ordering Code:

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
		IllumaTech	IPI06	Good	1	6	Dims down to 1%, minor flickering at LE with
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	SureSlide	6633-P	Good	1	6	Dims down to 1%, minor flickering at LE with :
		Vizia	VPI06-1LZ	Good	1	6	Dims down to 1%, minor flickering at LE with
		Toggler	TG-600	Good	1	6	Dims down to 1%, minor flickering at LE with
	Lutron	Lumea	LGCL-600	Good	1	6	Dims down to 1%, minor flickering at LE with
		Diva	DV-600	Good	1	6	Dims down to 1%, minor flickering at LE with
		Skylark	S-600	Good	1	6	Dims down to 1%, minor flickering at LE with
		Maestro	MAW-600	Good	4	6	Dims down to 1%, minor flickering at LE with
	Legrand	Titan	CD703-PW	Good	4	6	Dims down to 1%, minor flickering at LE with
		Harmony	D703-PTC	Good	3	6	Dims down to 1%, minor flickering at LE with
		Harmony	H703-PTC	Good	3	6	Dims down to 1%, minor flickering at LE with
		Harmony	11705-110	0000			Dinis down to 176, minor mekering at the with
		IllumaTech	IPL06	Best	1	6	Dims down to 1%
	Leviton	Sureslide	6674	Best	1	6	Dims down to 1%
			6672	Best			Dims down to 1% Dims down to 1%
		Decora			1	6	
CFL/LED	Lutron	Decora Slide	DSL06-1LZ	Best		6	Dims down to 1%
		Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
	Legrand	Radiant	RHCL453PW	Best	1	6	Dims down to 1%
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%
	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
		IllumaTech	IPE04	Good	1	6	Dims down to 1%
		Decora	6615-P	Good	1	6	Dims down to 20%
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%
Electronic Low Voltage		Diva	DVELV-300P	Best	1	6	Dims down to 1%
		Maestro	MAELV-600	Best	1	6	Dims down to 1%
		Skylark	SELVB-300P	Best	1	6	Dims down to 1%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
	Legrand	Scene Director	SCELV	Best	2	6	Dims down to 1%
	Legiand	Scene Director	JCLEV	DCSC			Dinis down to 1/6
		Vizia	VPM-06	Good	3	6	Dims down to 1%
Magnetic Low Voltage	Leviton	Decora	6613-P	Good	1	6	
					1		Dims down to 1%, minor flickering at LE with Desn't work with 1-6
	Lutron	Maestro	MALV-600	Not compatible	2	6	
		Harmony	DLV703-PW	Good			Dims down to 1%, minor flickering at LE with
	Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 1%
		In activities and	Tana			_	In
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 1%,
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 6%,
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 1%
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 20%,
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1%,
		Harmony	H703PTUTC	Good	1	6	Dims down to 20%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
Universal							
Universal		Adorne Touch	ADTH700MMTHM2	Rest	1		Dims down to 1%
Universal 	Cooper	Adorne Touch Decorator	ADTH700MMTUM2 DAL06P-C2-K-L	Best Good	1	6	Dims down to 1% Dims down to 1%, minor flickering at LE with

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating						
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.					
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.					
	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the lig level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.					
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.					
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.					
Low End (L.E.) Dead Travel						

Contact Information:
Bulbrite Industries Inc.
135 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSuppor@bulbrite.com
82/2/1 Bulbrite Industries Inc.
All Rights Reserved.