



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:	PARs Dimmable & Wet Rated: PAR38				
Item Number:	772740	772741	772742	772743	772744
Ordering Code:	LED15PAR38/NF25/827/WD	LED15PAR38/FL40/827/WD	LED15PAR38/WFL60/827/WD	LED15PAR38/NF25/830/WD	LED15PAR38/FL40/830/WD
Item Number:	772745	772746	772747	772748	
Ordering Code:	LED15PAR38/WFL60/830/WD	LED15PAR38/NF25/840/WD	LED15PAR38/FL40/840/WD	LED15PAR38/WFL60/840/WD	

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	2+ minimum load without ghosting
		SureSlide	6633-P	Good	1	6	2+ minimum load without ghosting
		Vizia	VPI06-1LZ	Bad	1	6	4+ minimum load without ghosting
	Lutron	Toggler	TG-600	Good	1	6	2+ minimum load without ghosting
		Diva	DV-600	Good	1	6	2+ minimum load without ghosting
		Lumea	LGCL-600	Good	1	6	2+ minimum load without ghosting
		Skylark	S-600	Good	1	6	2+ minimum load without ghosting
		Maestro	MAW-600	Bad	1	6	4+ minimum load without ghosting
	Legrand	Titan	CD703-PW	Good	1	6	2+ minimum load without ghosting, minor flicker at LE with 1
		Titan	CDLV703-PW	Best	1	6	
		Harmony	D703-PBKV	Good	1	6	2+ minimum load without ghosting
		Harmony	H703-PTC	Good	1	6	2+ minimum load without ghosting
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	
		Sureslide	6674	Best	1	6	
		Decora	6672	Best	1	6	
	Lutron	Diva	DVCL-153PL	Best	1	6	
		Toggler	TGCL-153PH	Best	1	6	
		Maestro	MACL-153MLH	Best	1	6	
		Skylark	CTCL-153	Best	1	6	
		Skylark	SCL-153P	Best	1	6	
	Legrand	Harmony	DCL453-PTC	Best	1	6	
		Harmony	HCL453PTC	Best	1	6	
		Adorne Paddle	ADPD453LW2	Best	1	6	
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Minor flicker at LE with 1-2
		IllumaTech	IPE04	Bad	1	6	Flicker at LE with 1-6
		Decora	6615-P	Bad	1	6	Dims down to 35%
	Lutron	Skylark	SELVB-300P	Good	1	6	
		Skylark Countour	CTELV-300P	Good	1	6	
		Diva	DVELV-300P	Good	1	6	
		Maestro	MAELV-600	Good	1	6	
		VIERTI	VTELV-600M-W	Best	1	6	
	Legrand	Scene Director	SECELV	Good	1	6	Dims down to 25%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Bad	1	6	3+ minimum load without ghosting, minor flicker at LE with 1
		Decora	6613-P	Best	1	6	
	Lutron	Maestro	MALV-600	Not Compatible	1	6	Doesn't turn on with 1-6
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	
		Miro Decorator	DRD4-W	Bad	1	6	Strobing at LE with 1-6
		Harmony	H703PTUTC	Good	1	6	Minor flicker at LE with 1-2
		Adorne Whisper	ADWR700MMTUW2	Bad	1	6	Strobing at LE with 1-6
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	
		Decorator	DAL06P-C2-K-L	Good	1	6	Shimmering at LE with 1-6
		Skye	SAL06P-W-K-L	Good	1	6	Shimmering at LE with 1-6

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact Information:
Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2017 Bulbrite Industries Inc.
All Rights Reserved.