



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:			
Item Number:	776690	776691	
Ordering Code:	LED4811/27K/FIL/D/B	LED4811/30K/FIL/D/B	
Item Number:			
Ordering Code:			

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPIO6	Good	1	6	Flickering at HE & L E with 1, Dims down to 1%
		SureSlide	6633-P	Best	1	6	Dims down to 1%
		Vizia	VPIO6-1LZ	Bad	2	6	Flickering at Med with 1 -2, Dims down to 1%
	Lutron	Toggler	TG-600	Good	1	6	Flickering at Med to LE with 1, flicker at LE with 5
		Diva	DV-600	Best	1	6	Dims down to 1%
		SkyLark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Good	5	6	Dims down to 1%
	Legrand	Titan	CD703-PW	Good	1	6	Flickering at HE with 1-4, dims down to 10%
		Harmony	D703-PTC	Good	1	6	Flickering at Med with 1 -3, flickering at LE with 4, Dims down to 3%
		Harmony	H703-PTC	Good	1	6	Flickering at Med with 1 -3, Dims down to 1%
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
	Lutron	Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%
		SkyLark	CTL-153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		SkyLark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
		Harmony	HCL453PTC	Best	1	6	Dims down to 1%
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 6%
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
		IllumaTech	IPE04	Best	1	6	Dims down to 1%
		Decora	6615-P	Best	1	6	Dims down to 1%
	Lutron	SkyLark Countour	CTELV-303P	Best	1	6	Dims down to 1%
		Diva	DVELV-300P	Best	1	6	Dims down to 1%
		Maestro	MAELV-600	Best	1	6	Dims down to 1%
		SkyLark	SELVB-300P	Best	1	6	Dims down to 1%
		VIERTI	VTELV-600M-W	Best	1	6	Dims down to 1%
	Legrand	Scene Director	SCELV	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6
	Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6
Decora			6613-P	Good	1	6	Flickering at Med with 1, dim down to 1%
Lutron		Maestro	MALV-600	Not Compatible	6	6	Doesn't turn on with 1-6
		Harmony	DLV703-PW	Best	1	6	Dims down to 1%
Legrand	Titan	DLV703-PW	Good	1	6	Flickering at HE with 3, dim down to 1%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 1%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 1%
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1				
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1				
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1%
		Harmony	H703PTUTC	Best	1	6	Dims down to 1%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 15%
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
		Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 1%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	ved: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact Information:
 Bulbrite Industries, Inc.
 145 West Commercial Avenue
 Moonachie, New Jersey 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708
 Email: ProductSupport@bulbrite.com
 ©2017 Bulbrite Industries, Inc.
 All Rights Reserved.