



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:

Item Number: 776699
Ordering Code: LED4B11/40K/FIL/D/B
Item Number:
Ordering Code:

		Lamps per Dimmer							
Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes			
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Dims down to 1%, flickering at LE with 1		
		SureSlide	6633-P	Best	1	6	Dims down to 1%		
		Vizia	VPI06-1LZ	Best	1	6	Dims down to 1%		
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 1%		
		Lumea	LGLCL-600	Best	1	6	Dims down to 1%		
		Diva	DV-600	Best	1	6	Dims down to 1%		
		Skylark	S-600	Best	1	6	Dims down to 1%		
		Maestro	MAW-600	Good	5	6	Dims down to 1%, flickering at LE with 1		
		Titan	CD703-PW	Good	1	6	Dims down to 1%, flickering at LE with 1-2		
	Legrand	Harmony	D703-PTC	Good	1	6	Dims down to 1%, flickering at LE with 1 - 2		
		Harmony	H703-PTC	Good	1	6	Dims down to 1%, flickering at LE with 1 - 2		
	CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%	
Sureslide			6674	Best	1	6	Dims down to 1%		
Decora			6672	Best	1	6	Dims down to 1%		
Decora Slide			DSL06-1LZ	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
Lutron		Skylark	CTCL-153	Best	1	6	Trim LE above 10% to avoid flickering		
		Diva	DVCL-153PL	Best	1	6	Trim LE above 10% to avoid flickering		
		Maestro	MACL-153MLH	Best	1	6	Trim LE above 10% to avoid flickering		
		Skylark	SCL-153P	Best	1	6	Trim LE above 10% to avoid flickering		
		Toggler	TGCL-153PH	Best	1	6	Trim LE above 10% to avoid flickering		
		Radio RA	RA2RR-6CL-PD	Best	1	6	Trim LE above 10% to avoid flickering		
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1%		
Legrand		Harmony	HCL453PTC	Best	1	6	Dims down to 1%		
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%		
Electronic Low Voltage		Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%	
			IllumaTech	IPE04	Best	1	6	Dims down to 1%	
	Decora		6615-P	Good	1	6	Dims down to 20%		
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%		
		Diva	DVELV-300P	Best	1	6	Dims down to 1%		
		Maestro	MAELV-600	Best	1	6	Dims down to 1%		
		Skylark	SELV-300P	Best	1	6	Dims down to 1%		
		VIERTI	VTELV-600M-W	Best	1	6	Dims down to 1%		
		Scene Director	SCELV	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
		Decora	6613-P	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
	Lutron	Maestro	MALV-600	Bad	5	6	Dims down to 1%, minor flickering at LE with 5-6		
		Harmony	DLV703-PW	Best	1	6	Dims down to 1%		
Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 1%, flickering at Med with 3			
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
		Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
		Decora Smart WiFi Technology	DW1KD	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
	GE	Z WAVE	ZW3005	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
Universal	Legrand	Adorne SoftTap	ADTP703TU	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
		Miro Decorator	DRD4-W	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
		Harmony	H703PTUTC	Best	1	6	Dims down to 10%		
		Adorne Whisper	ADWR700MMTUW2	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
		Adorne Touch	ADTH700MMTUM2	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		
		Skye	SAL06P-W-K-L	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6		

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact Information:
 Bulbrite Industries Inc.
 145 West Commercial Avenue
 Moonachie, New Jersey 07074
 PHONE: 1-800-526-5555
 FAX: 1-800-441-7708
 Email: ProductSupport@bulbrite.com
 ©2017 Bulbrite Industries Inc.
 All Rights Reserved.