



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:				
Item Number:	770615	770616	770619	770620
Ordering Code:	LED4GY6/30K/D/2	LED4GY6/27K/D/2	LED4DC/30K/D	LED4DC/27K/D
Item Number:				
Ordering Code:				

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Best	1	6	Dims down to 12% with 1-6
		SureSlide	6633-P	Best	1	6	Dims down to 5% with 1-6
		Vizia	VPI06-1LZ	Best	2	6	Dims down to 5% with 1-6
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 14% with 1-6
		Diva	DV-600	Best	1	6	Dims down to 4% with 1-6
		Skylark	S-600	Best	1	6	Dims down to 6% with 1-6
		Maestro	MAW-600	Good	3	6	Dims down to 6% with 3-6
	Legrand	Titan	CD703-PW	Good	1	6	Dims down to 22% with 1-6, flicker HE, Med & LE with 1
		Harmony	D703-PTC	Good	1	6	Dims down to 4% with 1-6, flicker HE, Med & LE with 1
		Harmony	H703-PTC	Good	1	6	Dims down to 6% with 1-6, flicker LE with 1-2
CFL/LED	Leviton	IllumaTech	IPL06	Good	1	6	Dims down to 1% with 1-6, minor flicker LE below 5%
		Sureslide	6674	Best	1	6	Dims down to 10% with 1-6
		Decora	6672	Best	1	6	Dims down to 10% with 1-6
	Lutron	Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 10% with 1-6
		Skylark	CTCL-153	Best	1	6	Set the dial above 3%, flicker happen with 3% below
		Diva	DVCL-153PL	Best	1	6	Set the dial above 3%, flicker happen with 3% below
		Maestro	MACL-153MLH	Best	1	6	Dims down to 10% with 1-6
		Skylark	SCL-153P	Best	1	6	Set the dial above 3%, flicker happen with 3% below
		Toggler	TGCL-153PH	Best	1	6	Set the dial above 3%, flicker happen with 3% below
	Legrand	Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 7% with 1-6
		Harmony	DCL453-PTC	Best	1	6	Dims down to 6% with 1-6
		Harmony	HCL453PTC	Best	1	6	Dims down to 11% with 1-6
		Adorne Paddle	ADPD453LM2	Bad	1	6	Dims down to 35% with 1-6
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 8% with 1-6
		IllumaTech	IPE04	Best	1	6	Dims down to 8% with 1-6
		Decora	6615-P	Good	1	6	Dims down to 41% with 1-6
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 8% with 1-6
		Diva	DVELV-300P	Best	1	6	Dims down to 8% with 1-6
		Maestro	MAELV-600	Best	1	6	Dims down to 8% with 1-6
		Skylark	SELVB-300P	Best	1	6	Dims down to 8% with 1-6
	Legrand	VIERTI	VTEL-600M-W	Best	1	6	Dims down to 8% with 1-6
Legrand	Scene Director	SCELV	Good	1	6	Dims down to 22% with 1-6	
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 9%, minor flicker LE with 2-6
		Decora	6613-P	Best	1	6	Dims down to 9% with 1-6
	Lutron	Maestro	MALV-600	Good	3	6	Dims down to 8% with 3-6
		Harmony	DLV703-PW	Good	1	6	Dims down to 5% with 1-6, minor flicker Med with 1-2
	Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 16% with 1-6, flicker Med & LE with 1-2
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 15% with 1-6
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 13% with 1-6
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 9% with 1-6
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 10% with 1-6
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1				
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1				
	GE	Z WAVE	ZW3005	Good	1	6	Dims down to 3% with 1-6, shimmering at LE with 1-6
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 20% with 1-6
		Miro Decorator	DRD4-W	Best	1	6	Set LE dimming at 5%to adviod LE flickering
		Harmony	H703PTUTC	Good	1	6	Dims down to 23% with 1-6
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Set LE dimming at 5%to adviod LE flickering
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Set LE dimming at 5%to adviod LE flickering
		Decorator	DAL06P-C2-K-L	Best	1	6	Set LE dimming at 5%to adviod LE flickering
Cooper	Skye	SAL06P-W-K-L	Best	1	6	Set LE dimming at 5%to adviod LE flickering	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 *May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact Information:
 Bulbrite Industries Inc.
 145 West Commercial Avenue
 Moonachie, New Jersey 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708
 Email: ProductSupport@bulbrite.com
 ©2019 Bulbrite Industries Inc.
 All Rights Reserved.