



345 West Commercial Ave. Moonachie, NJ 07074

## Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	GRAND LED FILAMENT							
<b>Item Number:</b>	776300	776301	776302	776303	776304	776305	776320	
<b>Ordering Code:</b>	LED4PSS2/22K/FIL	LED4ET25/22K/FIL	LED4G63/22K/FIL	LED4WB/22K/FIL	LED4BH/22K/FIL	LED4DIA/22K/FIL	LED4GLACIER/20K/FIL-NOS	
<b>Item Number:</b>	776306	776314	776316	776317	776318	776319		
<b>Ordering Code:</b>	LED4OLV/22K/FIL	LED4BT56/22K/FIL	LED4ICE/20K/FIL-NOS	LED4DROP/20K/FIL-NOS	LED4EWE/20K/FIL-NOS	LED4ORB/20K/FIL-NOS		

		Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06		Best	1	6	Dims down to 5% with 1-6	
		SureSlide	6633-P		Best	1	6	Dims down to 5% with 1-6	
		Vizia	VPI06-1LZ		Good	1	6	Dims down to 5% with 1-6, minor flicker at Med with 1	
		Toggler	TG-600		Best	1	6	Dims down to 5% with 1-6	
		Diva	DV-600		Best	1	6	Dims down to 5% with 1-6	
		SkyLark	S-600		Best	1	6	Dims down to 5% with 1-6	
	Lutron	Maestro	MAW-600		Good	2	6	Dims down to 5% with 2-6, shimmer at LE with 1-3	
		SkyLark	SCL-153P		Good	1	6	Dims down to 3% with 1-6, minor flicker at Med with 1-2	
		Maestro	MAW-600		Good	2	6	Dims down to 5% with 2-6, shimmer at LE with 1-3	
		SkyLark	SCL-153P		Good	1	6	Dims down to 3% with 1-6, minor flicker at Med with 1-2	
		Toggler	TGCL-153PH		Best	1	6	Dims down to 0.1% with 1-6	
		Radio RA	RA2R-6CL-PD		Best	1	6	Dims down to 5% with 1-6	
Legrand	Harmony	HCL453-PTC		Good	1	6	Dims down to 3% with 1-6, minor flicker at Med with 1-2		
	Harmony	H703-PTC		Good	1	6	Dims down to 3% with 1-6, minor flicker at Med with 1		
	Harmony	H703-PTC		Good	1	6	Dims down to 3% with 1-6, minor flicker at Med with 1		
CFL/LED	Leviton	IlumaTech	IPL06		Best	1	6	Dims down to 0.2% with 1-6	
		SureSlide	6674		Best	1	6	Dims down to 10% with 1-6	
		Decora	6672		Best	1	6	Dims down to 10G% with 1-6	
		SkyLark	CTCL-153		Best	1	6	Dims down to 0.1% with 1-6	
		Diva	DVCL-153PL		Best	1	6	Dims down to 0.1% with 1-6	
		Maestro	MACL-153MLH		Best	1	6	Dims down to 7% with 1-6	
	Lutron	SkyLark	SCL-153P		Best	1	6	Dims down to 0.1% with 1-6	
		Toggler	TGCL-153PH		Best	1	6	Dims down to 0.1% with 1-6	
		Radio RA	RA2R-6CL-PD		Best	1	6	Dims down to 5% with 1-6	
		Harmony	HCL453-PTC		Best	1	6	Dims down to 7% with 1-6	
		Harmony	HCL453-PTC		Best	1	6	Dims down to 9% with 1-6	
		Adorne Paddle	ADPD453LM2		Good	1	6	Dims down to 25% with 1-6	
	Electronic Low Voltage	Leviton	Vizia	VPE04		Good	1	6	Dims down to 13% with 1-6, minor flicker at Med with 1-6
			IlumaTech	IPE04		Good	1	6	Dims down to 10% with 1-6, minor flicker at Med with 1-6
			Decora	6615-P		Bad	1	6	dims down to 35% with 1-6,
SkyLark Countour			CTELV-303P		Good	1	6	Dims down to 10% with 1-6, minor flicker at Med with 1-6	
Lutron		Diva	DVELV-300P		Good	1	6	Dims down to 8% with 1-6, minor flicker at Med with 1-6	
		Maestro	MAELV-600		Good	1	6	Dims down to 10% with 1-6, minor flicker at Med with 1-6	
		SkyLark	SELVB-300P		Good	1	6	Dims down to 10% with 1-6, minor flicker at Med with 1-6	
		VIERTI	VTEL-600M-W		Best	1	6	Dims down to 10% with 1-6,	
		Scene Director	SCELV		Good	1	6	Dims down to 25% with 1-6	
		Magnetic Low Voltage	Leviton	Vizia	VPM-06		Good	2	6
Decora	6613-P				Best	1	6	Dims down to 10% with 1-6	
Lutron	Maestro		MALV-600		Good	2	6	Dims down to 7% with 1-6,	
	Harmony		DLV703-PW		Good	1	6	Dims down to 3% with 1-6, minor flicker at Med with 1	
	Titan		CDLV703-PW		Good	1	6	Dims down to 3% with 1-6, minor flicker at Med with 1	
Universal	Legrand	Adorne SoftTap	ADTP703TU		Best	1	6	Dims down to 12% with 1-6	
		Miro Decorator	DRD4-W		Best	1	6	Dims down to 3% with 1-6	
		Harmony	H703PTUTC		Best	1	6	Dims down to 12% with 1-6	
		Adorne Whisper	ADWR700MMTUM2		Best	1	6	Dims down to 0.1% with 1-6	
		Adorne Touch	ADTH700MMTUM2		Best	1	6	Dims down to 0.1% with 1-6	
		Decorator	DAL06P-CZ-K-L		Good	1	6	Dims down to 11% with 1-6, minor flicker at Med with 1	
	Cooper	Decorator	DAL06P-CZ-K-L		Good	1	6	Dims down to 11% with 1-6, minor flicker at Med with 1	
		Skye	SAL06P-W-K-L		Good	1	6	Dims down to 0.5% with 1-6, shimmer at LE with 1	

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.  
 †May experience "pop on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	

Contact Information:  
 Bulbrite Industries Inc.  
 345 West Commercial Avenue Moonachie, New Jersey 07074  
 PHONE: 1-800-528-5555 FAX: 1-800-443-7708  
 Email: Productsupport@bulbrite.com  
 ©2019 Bulbrite Industries Inc.  
 All Rights Reserved.