/est Commercial Ave. achie, NJ 07074								
Dimmer Compatibility Guide PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.								
luct Family Name:								
n Number: ering Code:	776733 LED5B11/27K/FIL/E26/3	776734 LED5B11/30K/FIL/E26/3	776735 LED5B11/27K/FIL/M/E26/3	776736 LED5B11/30K/FIL/M/E26/3				
Number: ering Code:								
enng Code:					Lamps p	er Dimmer		
	Manufacturer	Product	Model Number	Overall Rating	Recommended	Maximum Tested*	Notes	
	manaracturer	IllumaTech	IPI06	Best	Wiinimum 1	6	Dims down to 1%	
	Leviton	SureSlide	6633-P	Best	1	6	Dims down to 1%	
-		Vizia Toggler	VPI06-1LZ TG-600	Good Best	2	6	Dims down to 1% Dims down to 1%	
		Lumea	LGCL-600	Good	1	6	Dims down to 1% Dims down to 1%, minor flickering at HE with 1	
indescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)		Diva	DV-600	best	1	6	Dims down to 1%	
,,		Skylark	S-600	Best	4	6	Dims down to 1%	
-		Maestro Titan	MAW-600 CD703-PW	Good Good	4	6	Dims down to 1% Dims down to 1%	
	Legrand	Harmony	D703-PTC	Good	3	6	Dims down to 1%	
		Harmony	H703-PTC	Good	3	6	Dims down to 1%	
		IllumaTech	IPL06	Best	1	6	Dims down to 1%	
	Leviton	Sureslide	6674	Best	1	6	Dims down to 1%	
		Decora	6672	Best	1	6	Dims down to 1%	
_		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%	
	Lutron	Skylark Sunnata	CTCL-153 STCL - 153	Best Best	1	6	Dims down to 1% Dims down to 1%	
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%	
CFL/LED		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%	
		Skylark	SCL-153P	Best	1	6	Dims down to 1%	
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%	
	Legrand	Radio RA Harmony	RA2RR-6CL-PD DCL453-PTC	Best	1	6	Dims down to 1% Dims down to 1%	
		Radiant	RHCL453PW	Best	1	6	Dims down to 1%	
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%	
		Vizia	VPE04	Best	1	6	Dims down to 1%	
	Leviton	IllumaTech	IPE04	Not compatible	1	6	Cut down 70% dimming range	
		Decora	6615-P	Not compatible	1	6	Cut down 50% dimming range	
		Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%	
Electronic Low Voltage	Lutron	Diva Maestro	DVELV-300P MAELV-600	Best Best	1	6	Dims down to 1% Dims down to 1%	
		Skylark	SELVB-300P	Best	1	6	Dims down to 1%	
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%	
	Legrand	Scene Director	SCELV	Best	1	6	Dims down to 1%	
		Vizia	VPM-06	Good	2	6	Dims down to 1%	
Magnetic Low Voltage	Leviton	Decora	6613-P	Best	1	6	Dims down to 1%	
	Lutron	Maestro	MALV-600	Not compatible	1	6	Not turn on with 1-6	
	1	Harmony Titan	DLV703-PW CDLV703-PW	Good Good	2	6	Dims down to 1% Dims down to 1%	
	Legrand	litan	CDLV703-PW	Good	2	Б	Dims down to 1%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 1%	
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%	
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 1%	
	Lutron	Caseta Wireless smart dimmer Wi-Fi Caseta Wireless smart dimmer Wi-Fi	PD-10NXD PD-6WCL	Best Best	1	6	Dims down to 1% Dims down to 1%	
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%	
	Legrand	Adorne SofTap Miro Decorator	ADTP703TU DRD4-W	Good Good	2	6	Dims down to 5% Dims down to 1%,minor flickering HE with 1-6	
Universal		Miro Decorator Harmony	H703PTUTC	Good Not compatible	2	6	Dims down to 1%,minor flickering HE with 1-6 Off at LE with 2-6	
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%,	
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%	
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 1%, minor flickering at HE with 1	
		Skye	SAL06P-W-K-L	Good	1	6	Dims down to 1%, minor flickering at HE with 1	

Overall Rating					
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.				
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.				
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. Th periods of dead travel are minor and most of the time not visible. Minor audible noise.				
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.				
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.				
Low End (L.E.) Dead Travel	Determines now much in any dead daver exists at the top and bottom of the diminer strange. Dead daver is when the sinder can be more without aneuting the ngit revel.				

Contact Information: Bulbrite Industries Inc. 145 Wet Commercial Avenue Moonachie, New Jersey (7077 PhotMe: 1-900-224 5555 FAX: 1400-424-7708 FAX: 1400-424-7708 FAX: 1400-424-7708 FAX: 1400-424-7708 Junit Postchargon/Bulbrite.com xxxi z sustriet measures mc. J Rights Reserved.