



145 West Commercial Ave.
Moonachie, NJ 07074



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab controlled environment. Actual results may vary.

Product Family Name:	776626	776627	776628	776629	776632
Item Number:	LED581/27K/FL/E12/3	LED581/30K/FL/E12/3	LED5CA10/27K/FL/E12/3	LED5CA10/30K/FL/E12/3	LED4616/27K/FL/M/3
Ordering Code:					

		Lamps per Dimmer						
Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IP06	Best	1	6	Dims down to 0.1%	
		SureSlide	8623-P	Best	1	6	Dims down to 0.1%	
	Lutron	Visia	VPO6-1L2	Good	2	6	Dims down to 0.1%, minor flicker with 1-6	
		Toggle	TG-600	Best	1	6	Dims down to 0.1%	
		Olva	OV-600	Best	1	6	Dims down to 0.1%	
		SkyLark	S-600PH	Best	1	6	Dims down to 0.1%	
	Legrand	Maestro	MAWV-600	Good	4	6	Dims down to 0.2%	
		Titan	CD703-PW	Good	4	6	Dims down to 0.1%, flicker at LE with 4-5	
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1%, flicker at Med with 1-3	
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1%, flicker at HE with 1	
CFL, LED	Leviton	IllumaTech	IP06	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-4	
		SureSlide	8674	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Lutron	Decora	8672	Best	1	6	Dims down to 0.1%	
		SkyLark	SCTLS-153	Best	1	6	Dims down to 0.1%	
		Olva	DVCL-153PL	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Maestro	MAELV-153MLH	Best	1	6	Dims down to 0.1%	
	Legrand	Toggle	TGCL-153PH	Best	1	6	Dims down to 0.1%	
		Radio RA	RA2R8-6CL-PD	Best	1	6	Dims down to 0.1%	
		Harmony	HCL453-PTC	Good	2	6	Dims down to 0.1%, minor flicker at LE & Med with 1 & Med1-2	
		Adorne Paddle	ADPO45-ILM2	Good	2	6	Dims down to 0.1%	
Electronic Low Voltage	Leviton	Visia	VPE04	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		IllumaTech	IPED4	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Lutron	Skidell's Countour	8615-P	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
		Olva	DVELV-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Maestro	MAELV-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		SkyLark	SLELV-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Legrand	Scene Director	SCELV	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
	Magnetic Low Voltage	Leviton	Visia	VPM-06	Good	3	6	Dims down to 1%, flicker at HE with 1-3
			Decora	8613-P	Good	1	6	Dims down to 1%, flicker at HE with 1-3
Lutron		Maestro	MALV-600	Bad	5	6	Dims down to 1%	
		Harmony	DLV703-PW	Good	1	6	Dims down to 10%, flicker at LE with 1-6	
Legrand	Titan	COLV703-PW	Good	1	6	Dims down to 10%, flicker at LE with 1-6		
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMK1-8L2	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Decora Smart Wi-Fi	DDKH-1B2	N/A				
	Lutron	SwitchLIn Remote Control dimmer		N/A				
		Caesars Wireless Smart dimmer Wi-Fi	PD-04NCL	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Legrand	Adorne Touch Wi-Fi TRU Universal	ADTP7008MTUW1	N/A				
		Adorne Sol Top Wi-Fi TRU Universal	ADTP7008MTUW1	N/A				
GE	Z-WAVE	ZW3005	Good			Dims down to 10%, minor flicker at LE with 2-6		
Universal	Legrand	Adorne SoftTap	ADTP701TLU	Best	1	6	Dims down to 1%	
		Miro Decorator	DRD4-W	Good	1	6	Dims down to 1%, flicker at LE with 1-3	
		Harmony	H703PTUTC	Best	1	6	Dims down to 1%	
		Adorne Whisper	ADWP700MMTUW2	Best	1	6	Dims down to 0.1%	
	Cooper	Adorne Touch	ADTP700MTUW2	Best	1	6	Dims down to 0.1%	
		Decorator	DALOP-C2-K-L	Good	1	6	Dims down to 1%, minor flicker at LE & Med with 1-6	
	Skye	SALOP-W-K-L	Good	1	6	Dims down to 1%, minor flicker at LE & Med with 1-6		

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on" lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

Bulbrite Industries Inc.
 145 West Commercial Avenue
 Moonachie, New Jersey 07074
 Phone: 1-800-228-5555
 Fax: 1-800-441-7738
 Email: ProductSupport@bulbrite.com
 ©2017 Bulbrite Industries Inc.
 All Rights Reserved.