



345 West Commercial Ave.
Moonachie, NJ 07074



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab controlled environment. Actual results may vary.

Product Family Name:	776626	776627	776628	776629	776612
Item Number:	LEDSB11/27K/FL/E12/3	LEDSB11/30K/FL/E12/3	LEDSCA10/27K/FL/E12/3	LEDSCA10/30K/FL/E12/3	LED4616/27K/FL/M/3
Ordering Code:					

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
					Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	BurnaTech	IP06	Best	1	6	Dims down to 0.1%	
		SureSlide	8633-P	Best	1	6	Dims down to 0.1%	
	Lutron	Visia	VPO06-1LZ	Good	2	6	Dims down to 0.1%, minor flicker with 1-6	
		Toggle	TG-600	Best	1	6	Dims down to 0.1%	
		Divva	DV-600	Best	1	6	Dims down to 0.1%	
		Skyark	S-600PH	Best	1	6	Dims down to 0.1%	
	Legrand	Maestro	MAW-600	Good	4	6	Dims down to 0.2%	
		Titan	CD703-PW	Good	4	6	Dims down to 0.1%, flicker at LE with 4-5	
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1%, flicker at Med with 1-3	
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1%, flicker at HE with 1	
CFL/LED	Leviton	BurnaTech	IP06	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-4	
		SureSlide	6674	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Lutron	Decora	6672	Best	1	6	Dims down to 0.1%	
		Skyark	SKEL-153	Best	1	6	Dims down to 0.1%	
		Divva	DVCL-153PL	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Maestro	MAEL-153MLH	Best	1	6	Dims down to 0.1%	
	Legrand	Skyark	SCL-153P	Best	1	6	Dims down to 0.1%	
		Toggle	TGCL-153PH	Good	2	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Radio SA	RA298-GCL-PD	Best	1	6	Dims down to 0.1%	
		Harmony	DCL453-PTC	Good	2	6	Dims down to 0.1%, minor flicker at LE & Med with 1 & Med1-2	
Electronic Low Voltage	Leviton	Visia	VPE04	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		BurnaTech	IPED4	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Lutron	Decora	8615-P	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
		Skyark Countour	CELV-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Divva	DVELV-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Maestro	MAELV-600	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Legrand	Skyark	SELV-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		VESTI	VTEL-600M-W	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
		Scene Director	SELV	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
Magnetic Low Voltage	Leviton	Visia	WPM-06	Good	3	6	Dims down to 1%, flicker at HE with 1-3	
		Decora	6613-P	Good	1	6	Dims down to 1%, flicker at HE with 1-3	
	Legrand	Maestro	MALV-600	Bad	5	6	Dims down to 1%	
		Harmony	DLV703-PW	Good	1	6	Dims down to 10%, flicker at LE with 1-6	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMK1-1BZ	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Decora Smart Wi-Fi	DK6HD-1BZ	N/A				
	Lutron	Insteon	SwitchLin Remote Control dimmer	N/A				
		Castro Wireless smart dimmer Wi-Fi	FW-DWCL	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Legrand	Adorne touch Wi-Fi TRU Universal	ADT1700RMTUW1	N/A				
		Adorne Soft Tap Wi-Fi TRU Universal	ADT1700RMTUW1	N/A				
	GE	Z-WAVE	ZW3005	Good			Dims down to 10%, minor flicker at LE with 2-6	
	Universal	Legrand	Adorne SoftTap	ADT1703TU	Best	1	6	Dims down to 1%
			Miro Decorator	DRD4-W	Good	1	6	Dims down to 1%, flicker at LE with 1-3
Harmony			H703PTUC	Best	1	6	Dims down to 1%	
Adorne Whisper			ADW1700MFTUW2	Best	1	6	Dims down to 0.1%	
Cooper		Adorne Touch	ADT1700MFTUW2	Best	1	6	Dims down to 0.1%	
		Decorator	DALDEP-C2-K-L	Good	1	6	Dims down to 1%, minor flicker at LE & Med with 1-6	
		Skye	SALDEP-W-K-L	Good	1	6	Dims down to 1%, minor flicker at LE & Med with 1-6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on" lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Bulbrite Industries Inc.
 345 West Commercial Avenue
 Moonachie, New Jersey 07074
 Phone: 1-800-328-5555
 Fax: 1-800-441-7738
 Email: ProductSupport@bulbrite.com
 ©2017 Bulbrite Industries Inc.
 All Rights Reserved.