



145 West Commercial Ave. Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:
 Item Number: 776881 776892
 Ordering Code: LED5T9/27K/FIL/3 LED5T9/30K/FIL/3
 Item Number:
 Ordering Code:

							Lamps per Dimmer	
Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Best	1	6	Dims down to 15% with 1-6	
		SureSlide	6633-P	Best	1	6	Dims down to 15% with 1-6	
		Vizia	VPID6-1LZ	Good	2	6	Dims down to 15% with 1-6	
	Lutron	Toggle	TG-600	Best	1	6	Dims down to 15% with 1-6	
		Diva	DV-600	Best	1	6	Dims down to 15% with 1-6	
		Skylark	S-600	Best	1	6	Dims down to 15% with 1-6	
		Maestro	MAAW-600	Good	2	6	Dims down to 15% with 1-6	
	Legrand	Titan	CD03-PW	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1	
		Harmony	D703-PTC	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1	
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1	
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 1% with 1-6	
		SureSlide	6674	Best	1	6	Dims down to 8% with 1-6	
		Decora	6672	Best	1	6	Dims down to 6% with 1-6	
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 0.1% with 1-6	
		Diva	DVCL-153PL	Best	1	6	Dims down to 0.1% with 1-6	
		Maestro	MACL-153MLH	Best	1	6	Dims down to 4% with 1-6	
		Maestro	SCL153P	Best	1	6	Dims down to 0.1% with 1-6	
		Toggle	TGCL-153PH	Best	1	6	Dims down to 0.1% with 1-6	
		Radio RA	RA2RR-ECL-PO	Best	1	6	Dims down to 2% with 1-6	
	Legrand	Harmony	DCL433-PTC	Best	1	6	Dims down to 4% with 1-6	
		Harmony	HCL433PTC	Best	1	6	Dims down to 10% with 1-6	
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 32% with 1-6	
		Vizia	VPID4	Best	1	6	Dims down to 13% with 1-6	
Electronic Low Voltage	Leviton	IlumaTech	IPE04	Best	1	6	Dims down to 8% with 1-6	
		Decora	6615-P	Bad	1	6	Dims down to 42% with 1-6	
		Skylark Countour	CTELV-303P	Best	1	6	Dims down to 10% with 1-6	
	Lutron	Diva	DVELV-300P	Best	1	6	Dims down to 10% with 1-6	
		Maestro	MAELV-600	Best	1	6	Dims down to 10% with 1-6	
		Skylark	SELVB-300P	Best	1	6	Dims down to 10% with 1-6	
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 10% with 1-6	
	Legrand	Scene Director	SCELV	Good	1	6	Dims down to 30% with 1-6	
	Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 6% with 2-6
			Decora	6613-P	Best	1	6	Dims down to 10% with 1-6
Lutron		Maestro	MALV-600	Good	3	6	Dims down to 5% with 3-6	
		Harmony	HDV703-PW	Best	1	6	Dims down to 0.1% with 1-6	
		Titan	CDLV703-PW	Best	1	6	Dims down to 15% with 1-6	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 20% with 1-6	
	Leviton	Decora Smart Wi-Fi	DDXH4-1BZ					
	Insteon	SwitchLin Remote Control dimmer						
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 5% with 1-6	
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1					
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1					
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1% with 1-6	
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	Dims down to 20% with 1-6	
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1% with 1-6	
		Harmony	H703PTUTC	Good	1	6	Dims down to 30% with 1-6	
		Adorne Whisper	ADWR700MMTUM2	Best	1	6	Dims down to 1% with 1-6	
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1% with 1-6	
		Decorator	DAL06P-C2-K-1	Best	1	6	Dims down to 1% with 1-6	
	Skye	SAL06P-W-K-1	Best	1	6	Dims down to 1% with 1-6		

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact Information:
 Bulbrite Industries Inc.
 145 West Commercial Avenue Moonachie, New Jersey 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708
 Email: ProductSupport@bulbrite.com

©2019 Bulbrite Industries Inc.
 All Rights Reserved.