



145 West Commercial Ave.  
Moonachie, NJ 07074

## Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	776634	776635
<b>Item Number:</b>	LED5T9/27K/FIL/D/B	LED5T9/30K/FIL/D/B
<b>Ordering Code:</b>		
<b>Item Number:</b>		
<b>Ordering Code:</b>		

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		SureSlide	6633-P	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Vizia	VPI06-1LZ	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
	Lutron	Toggler	TG-600	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Lumea	LGCL-600	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Diva	DV-600	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Skylark	S-600	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Maestro	MAW-600	Bad	3	6	Flickering at LE with 1-6, dims down to 1%
	Legrand	Titan	CD703-PW	Bad	3	6	Flickering at LE with 1-6, dims down to 1%
		Harmony	D703-PTC	Bad	3	6	Flickering at LE with 1-6, dims down to 1%
		Harmony	H703-PTC	Bad	3	6	Flickering at LE with 1-6, dims down to 1%
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
	Legrand	Radiant	RHCL453PW	Best	1	6	Dims down to 1%
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		IllumaTech	IPE04	Not compatible	1	6	No dimming range
		Decora	6615-P	Not compatible	1	6	No dimming range
	Lutron	Skylark Countour	CTELV-303P	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Diva	DVELV-300P	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Maestro	MAELV-600	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Skylark	SELVB-300P	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		VIERTI	VTEL-600M-W	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
		Scene Director	SCELV	Bad	1	6	Flickering at HE with 1-6
	Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6
Decora			6613-P	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
Lutron		Maestro	MALV-600	Not compatible	1	6	Doesn't turn on with 1-6
		Harmony	DLV703-PW	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
Legrand		Titan	CDLV703-PW	Good	1	6	Minor flickering at LE with 1-6, dims down to 1%
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 5%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 5%
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 5%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 1%
	GE	Z WAVE	ZW3005	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6
Universal	Legrand	Adorne SoftTap	ADTP703TU	Bad	3	6	Dims down to 30%
		Miro Decorator	DRD4-W	Bad	1	6	Flickering at HE with 1-6
		Harmony	H703PTUTC	Bad	3	6	Dims down to 30%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6
		Skye	SAL06P-W-K-L	Good	1	6	Dims down to 1%, minor flickering at LE with 1-6

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	

**Contact Information:**  
 Bulbrite Industries Inc.  
 145 West Commercial Avenue  
 Moonachie, New Jersey 07074  
 PHONE: 1-800-528-5555  
 FAX: 1-800-441-7708  
 Email: ProductSupport@bulbrite.com  
 © 2017 Bulbrite Industries Inc.  
 All Rights Reserved.