



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:

Item Number:	772261	772262	772265	772266
Ordering Code:	LED6PAR20/NFL25/927/WD/2	LED6PAR20/FL40/927/WD/2	LED6PAR20/NFL25/930/WD/2	LED6PAR20/FL40/930/WD/2
Item Number:				
Ordering Code:				

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Dims down to 20%
		SureSlide	6633-P	Best	1	6	Dims down to 8%
		Vizia	VPI06-1LZ	Good	4	6	Dims down to 11%
	Lutron	Toggler	TG-600	Good	1	6	Dims down to 16%
		Lumea	LGCL-600	Good	1	6	Dims down to 15%
		Divva	DV-600	Best	1	6	Dims down to 5%
		SkyLark	S-600	Best	1	6	Dims down to 10%
	Legrand	Maestro	MAW-600	Good	3	6	Dims down to 6%
		Titan	CD703-PW	Good	1	6	Dims down to 15%, minor flicker LE with 1
		Harmony	D703-PTC	Best	1	6	Dims down to 3%
		Harmony	H703-PTC	Best	1	6	Dims down to 8%
CFL/LED	Leviton	IllumaTech	IPI06	Best	1	6	Dims down to 3%
		Sureslide	6674	Good	1	6	Dims down to 14%
		Decora	6672	Good	1	6	Dims down to 13%
	Lutron	Decora Slide	DSL06-1LZ	Good	1	6	Dims down to 14%
		SkyLark	CTCL-153	Best	1	6	Dims down to 2%
		Divva	DVCL-153PL	Best	1	6	Dims down to 2%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 10%
	Legrand	SkyLark	SCL-153P	Best	1	6	Dims down to 2%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 2%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 9%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 8%
		Harmony	HCL453PTC	Good	1	6	Dims down to 15%
		Adorne Paddle	ADPD453LM2	Bad	1	6	Dims down to 33%
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Dims down to 16%
		IllumaTech	IPE04	Good	1	6	Dims down to 13%
		Decora	6615-P	Good	1	6	Dims down to 41%
	Lutron	SkyLark Countour	CTELV-303P	Good	1	6	Dims down to 15%
		Divva	DVELV-300P	Good	1	6	Dims down to 15%
		Maestro	MAELV-600	Good	1	6	Dims down to 13%
		SkyLark	SELV-300P	Good	1	6	Dims down to 15%
	Legrand	VIERTI	VTEL-600M-W	Good	1	6	Dims down to 15%
		Scene Director	SCELV	Bad	1	6	Dims down to 30%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	4	6	Dims down to 11%
		Decora	6613-P	Good	1	6	Dims down to 10%
	Lutron	Maestro	MALV-600	Good	4	6	Dims down to 11%
		Harmony	DLV703-PW	Best	1	6	Dims down to 5%
	Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 15%
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Dims down to 19%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Dimd down to 15%
	Leviton	Decora Smart WiFi Technology	DW1KD	Good	1	6	Dimd down to 15%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dimd down to 13%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dimd down to 11%
GE	Z WAVE	ZW3005	Best	1	6	Dims down to 4%	
Universal	Legrand	Adorne SoftTap	ADTP703TU	Good	1	6	Dims down to 22%
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1%
		Harmony	H703PTUTC	Good	1	6	Dims down to 37%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 5%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 5%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various ratings, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 10% or less of light output.
High End (H.E.) Dead Travel	
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

Contact Information:
Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2017 Bulbrite Industries Inc.
All Rights Reserved.