



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: 776611 776668 776669
Item Number: LED7G25/27K/FL/M/3 LED7A19/30K/FL/2 LED7S118/30K/FL/2
Ordering Code:

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes
					Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IP06	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%
		SureSlide	8633-P	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%
		Vizia	VPI06-1L2	Good	1	6	Minor flicker 1-50% with 1, dims down to 0.1%
	Lutron	Toggle	TG-600	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%
		Diva	DV-600	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%
		Skylark	S-600	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%
		Maestro	MAW-600	Good	4	6	Minor flicker at LE with 1-6, dims down to 0.2%
	Legrand	Titan	CD703-PW	Good	1	6	Minor flicker at LE with 1-3 dims down to 0.1%
		Harmony	H703-PTC	Good	1	6	Minor flicker at LE with 1-2, dims down to 0.1%
		Harmony	H703-PTC	Good	1	6	Minor flicker at LE with 1-2, dims down to 0.1%
CFI/LED	Leviton	IlumaTech	IP106	Best	1	6	Dims down to 0.1% with 1-6
		SureSlide	6674	Best	1	6	Dims down to 0.1% with 1-6
		Decora	6672	Best	1	6	Dims down to 0.1% with 1-6
	Lutron	Skylark Countour	CTCL-153	Best	1	6	Dims down to 0.1% with 1-6
		Diva	DVCL-153PL	Best	1	6	Dims down to 0.1% with 1-6
		Maestro	MACL-153MLH	Best	1	6	Dims down to 0.1% with 1-6
		Skylark	SCL-153P	Best	1	6	Dims down to 0.1% with 1-6
	Legrand	Toggle	TGCL-153PH	Best	1	6	Dims down to 0.1% with 1-6
		Radio RA	RA2R-6CL-PD	Best	1	6	Dims down to 0.1% with 1-6
		Harmony	DCL453-PTC	Best	1	6	Dims down to 0.1% with 1-6
Legrand	Harmony	HCL453PTC	Best	1	6	Dims down to 0.1% with 1-6	
	Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 0.1% with 1-6	
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%
		IlumaTech	IP04	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%
		Decora	6615-P	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%
	Lutron	Skylark Countour	CTELV-303P	Good	1	6	Minor flicker at Med with 1-4, dims down to 0.1%
		Diva	DVELV-300P	Good	1	6	Minor flicker at Med with 1-4, dims down to 0.1%
		Maestro	MAELV-600	Good	1	6	Minor flicker at Med with 1-4, dims down to 0.1%
		Skylark	SELV-300P	Good	1	6	Minor flicker at Med with 1-4, dims down to 0.1%
	Legrand	VIZRTI	VTCL-600M-W	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%
		Scene Director	SCELV	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	Flicker LE - HE with 1, dims down to 0.1%
		Decora	6613-P	Good	1	6	Minor flicker from 10-50% with 1, dims down to 0.1%
	Lutron	Maestro	MALV-600	Bad	5	6	Dims down to 1% with 5-6
		Harmony	DLV703-PW	Good	1	6	Flicker LE - Med with 1, dims down to 0.1%
Legrand	Titan	CDLV703-PW	Good	1	6	Flicker LE with 1, dims down to 0.1%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BL2	Best	1	6	Dims down to 2%
		Decora Smart Wi-Fi	DDSD-182	N/A			
	Insteon	SwitchLin Remote Control dimmer		N/A			
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Bad	1	6	Flashing at LE with 1, minor flicker at LE with 2-6
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A			
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	Dims down to 0.1%
		Miro Decorator	DRD4-W	Bad	1	6	Turn on with flash with 1-3, dims down to 0.1% with 4-6
		Harmony	H703PTUC	Best	1	6	Dims down to 0.1%
		Adorne Whisper	ADW700RMTUW2	Best	1	6	Dims down to 0.1%
	Cooper	Adorne Touch	ADTH700MTUW2	Best	1	6	Dims down to 0.1%
		Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%
	Skye	SAL06P-W-K-L	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	