



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:				
Item Number:	776631	776632	776633	776698
Ordering Code:	LED7ST18/40/FIL/D/B	LED7G25/40K/FIL/D/B	LED7G25/40K/FIL/M/D/B	LED7A19/40K/FIL/D/B
Item Number:				
Ordering Code:				

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum		Notes	
					Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		SureSlide	6633-P	Best	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Vizia	VPI06-1LZ	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Toggler	TG-600	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Lumea	LGCL-600	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Diva	DV-600	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	Lutron	Skylark	S-600	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Maestro	MAW-600	Good	4	6	Dims down to 1%, minor flicker at LE with 1-6	
		Titan	CD703-PW	Bad	1	6	Dims down to 1%, flicker at Med with 1 & flicker at LE with 2-6	
		Harmony	D703-PTC	Good	1	6	Dims down to 1%, flicker at Med with 1 & flicker at LE with 2-6	
		Harmony	H703-PTC	Good	1	6	Dims down to 1%, flicker at Med with 1 & flicker at LE with 2-6	
		Legrand						
CFL/LED	Leviton	IlumaTech	IPI06	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		SureSlide	6674	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Decora	6672	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Decora Slide	DSL06-1LZ	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Skylark	CTCL-153	Best	1	6	Dims down to 1%	
	Lutron	Diva	DVCL-153PL	Best	1	6	Dims down to 1%	
		Maestro	MAEL-153MLH	Best	1	6	Dims down to 1%	
		Skylark	SCL-153P	Best	1	6	Dims down to 1%	
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%	
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%	
	Legrand	Harmony	HCL453-PTC	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Harmony	HCL453PTC	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 4%, minor flicker at LE with 1-6	
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		IlumaTech	IPE04	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Decora	6615-P	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
	Lutron	Skylark Countour	CTELV-303P	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Diva	DVELV-300P	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Maestro	MAELV-600	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Skylark	SELV-300P	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		VIERTI	VTEL-600M-W	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Scene Director	SCELV	Good	1	6	Dims down to 4%, minor flicker at LE with 1-6	
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	3	6	Dims down to 1%, minor flicker at Med with 1 & minor flicker at LE with 2-6	
		Decora	6613-P	Good	1	6	Dims down to 1%, minor flicker at Med with 1	
	Lutron	Maestro	MALV-600	Bad	5	6	Dims down to 1%, minor flicker at LE with 5-6	
		Harmony	DLV703-PW	Good	1	6	Dims down to 1%, minor flicker at Med with 1	
		Titan	CDLV703-PW	Good	1	6	Dims down to 1%, minor flicker at Med with 1 & minor flicker at LE with 2-6	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-8LZ	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	Leviton	Decora Smart WiFi Technology	DW1KD	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	GE	Z WAVE	ZW3005	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
Universal	Legrand	Adorne SoftTap	ADTP703TU	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Miro Decorator	DRD4-W	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Harmony	H703PTUTC	Bad	1	6	Dims down to 20%, minor flicker at LE with 1-6	
		Adorne Whisper	ADWR700MMTUW2	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Adorne Touch	ADTH700MMTUW2	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
		Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	Cooper	Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%, minor flicker at LE with 1-6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

Contact Information:
Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-443-7708
Email: ProductSupport@bulbrite.com
© 2017 Bulbrite Industries Inc.
All Rights Reserved.