



345 West Commercial Ave.  
Lansdale, PA 19382

### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility data is based on testing conducted by the manufacturer in a lab controlled environment. Actual results may vary.

<b>Product Family Name:</b>	772751	772752	772755	772756
<b>Item Number:</b>	LED7PAR20/NF25/827/WD/2	LED7PAR20/FL40/827/WD/2	LED7PAR20/NF25/830/WD/2	LED7PAR20/FL40/830/WD/2
<b>Ordering Code:</b>				
<b>Item Number:</b>				
<b>Ordering Code:</b>				

Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
				Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IP06	Best	1	6	
		SureSlide	6633-P	Best	1	6	
		Vizia	VP06-1LZ	Best	1	6	
	Lutron	Topgler	TO-600	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
		Lumea	LGCL-600	Best	1	6	
		Diva	DV-600	Best	1	6	
		SkyLark	S-600	Best	1	6	
		Maestro	MAW-600	Good	3	6	Dims down to 1%, flicker at LE with 3-6
		Titan	CD703-PW	Bad	1	6	Dims down to 2%, flicker at HE with 1 and Med with 2, flicker at LE with 2-6
	Legrand	Harmony	D703-PTC	Bad	1	6	Dims down to 1%, flicker HE & LE with 1, flicker at LE with 2
		Harmony	H703-PTC	Bad	1	6	Dims down to 1%, flicker HE & LE with 1, flicker at LE with 2
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	
		SureSlide	6674	Best	1	6	
		Decora	6672	Best	1	6	
	Lutron	Decora Slide	DSL06-1LZ	Best	1	6	
		SkyLark	CTCL-153	Best	1	6	
		Diva	DVCL-153PL	Best	1	6	
		Maestro	MACL-153MLH	Best	1	6	
		SkyLark	SCL-153P	Best	1	6	
		Topgler	TGCL-153PH	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
	Legrand	Radio RA	RA309-6CL-PO	Best	1	6	
		Harmony	DCL453-PTC	Best	1	6	
		Harmony	HCL453PTC	Best	1	6	
	Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 15%	
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	
		IlumaTech	IPED04	Best	1	6	
		Decora	6615-P	Best	1	6	
	Lutron	SkyLark Countour	CTELV-303P	Best	1	6	
		Diva	DVELV-300P	Best	1	6	
		Maestro	MALV-600	Best	1	6	
Legrand	SkyLark	SELV8-300P	Best	1	6		
	VIERTI	VTEL-600M-W	Best	1	6		
	Scene Director	SCELV	Best	1	6	Dims down to 2%	
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	
		Decora	6613-P	Best	1	6	
	Lutron	Maestro	MALV-600	Not Compatible	1	6	Not turn on with 1-6
		Harmony	DVL703-PW	Good	1	6	Dims down to 1%, flicker at LE with 1-6
Legrand	Titan	CDLV703-PW	Bad	1	6	Dims down to 1%, flicker at LE with 1, minor flicker at LE with 2-6	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	
		Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
	Lutron	Decora Smart WiFi Technology	DW1KD	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
		Caseta Wireless smart dimmer Wi-Fi	PD-10XND	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
	GE	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
		Z-WAVE	ZW3005	Best	1	6	dims down to 1%
Universal	Legrand	Adorne SoftTap	ADTF703TU	Best	1	6	
		Mina Decorator	DBD4-W	Good	1	6	Dims down to 1%, minor flicker LE with 1-6
		Harmony	H703PTUTC	Good	1	6	Dims down to 20%
		Adorne Whisper	ADAW700MMTUW2	Good	1	6	Dims down to 1%, minor flicker LE with 1-6
	Cooper	Adorne Touch	ADTF700MMTUW2	Good	1	6	Dims down to 1%, minor flicker LE with 1-6
		Decorator	DAL05P-C2-K-L	Good	1	6	Dims down to 1%, minor flicker LE with 1-6
		Skye	SAL06P-W-K-L	Good	1	6	Dims down to 1%, minor flicker LE with 1-6

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.  
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

<b>Overall Rating</b>	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise may be present.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise, typically less than 25 dB(A), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	

CONTACT INFORMATION:  
 Bulbrite Industries, Inc.  
 345 West Commercial Avenue  
 Lansdale, PA 19382  
 PHONE: 1-800-538-2555  
 FAX: 1-480-441-7158  
 Email: ProductSupport@bulbrite.com  
 ©2017 Bulbrite Industries, Inc.  
 All Rights Reserved.