



### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	MRs Dimmable & Enclosed Rated										
<b>Item Number:</b>	771301	771302	771303	771304	771305	771306	771307	771308	771309	771310	
<b>Ordering Code:</b>	LED8MR16SP15/50/827/D	LED8MR16NF25/50/827/D	LED8MR16FL35/50/827/D	LED8MR16WFL50/50/827/D	LED8MR16SP15/50/830/D	LED8MR16NF25/50/830/D	LED8MR16FL35/50/830/D	LED8MR16WFL50/50/830/D	LED8MR16NF25/50/850/D	LED8MR16FL35/50/850/D	
<b>Item Number:</b>	771312	771313	771316	771317	771321	771322	771323	771324	771325	771326	
<b>Ordering Code:</b>	LED8MR16NF25/50/927/D	LED8MR16FL35/50/927/D	LED8MR16NF25/50/930/D	LED8MR16FL35/50/930/D	LED9MR16SP15/75/827/D	LED9MR16NF25/75/827/D	LED9MR16FL35/75/827/D	LED9MR16WFL50/75/827/D	LED9MR16SP15/75/830/D	LED9MR16NF25/75/830/D	
<b>Item Number:</b>	771327	771328	771332	771333	771336	771337					
<b>Ordering Code:</b>	LED9MR16FL35/75/830/D	LED9MR16WFL50/75/830/D	LED9MR16NF25/75/927/D	LED9MR16FL35/75/927/D	LED9MR16NF25/75/930/D	LED9MR16FL35/75/930/D					

DIMMERS		Lutron DIVA DVELV-300P	Lutron Skylark SELV-300P	Lutron Contour CTELV-300	Lutron Vienti VTELV-600M-W	Lutron Maestro MAELV-600	Leviton Illumatech IPE04	Leviton Sureslide 6615 - POW	Leviton Vizia VPE04-1LZ	Legrand Adorne ADTP703TUW4	Legrand Adorne ADTH700MMTUW2
TRANSFORMERS	Hatch RS12-60M/LED	+	+	+	✓	+	+ -	+	✓	✓	✓
	Hatch RS12-60W	F LE 1-2	F LE 1-2	F LE 1-2	✓	F LE 1-2	F LE 1-6	Dim 35% 1-6	F LE	✓	✓
	Hatch VS12-60WD	+	+	+	✓	+	F LE 1-6	Dim 35% 1-6	F LE	✓	✓
	Hatch RS12-60M	F LE 1-2	F LE 1-2	F LE 1-2	✓	F LE 1-2	F LE 1-6	Dim 35% 1-6	F LE	✓	✓
	Hatch RS12-80M	+	+	+	✓	+	F LE 1-6	Dim 35% 1-6	F LE	✓	✓
	Lightech LET60LW	F LE 1-2	F LE 1-2	F LE 1-2	✓	F LE 1-2	F LE 1-6	Dim 35% 1-6	F LE	✓	✓
	Lightech LET75	+	+	+	✓	+	F LE 1-6	Dim 35% 1-6	F LE	✓	✓
	WAC EN-1260-R2	✓	✓	✓	✓	✓	F LE 1-6	Dim 35% 1-6	✓	✓	✓
	WAC EN-1260-R-AR	✓	✓	✓	✓	✓	F LE 1-6	Dim 35% 1-6	✓	✓	✓
	WAC EN-1275-R-AR	✓	✓	✓	✓	✓	F LE 1-6	Dim 35% 1-6	✓	✓	✓
	WAC EN-12100-R-AR	F M 1	F M 1	F M 1	✓	F M 1	F LE 1-6	Dim 35% 1-6	✓	F LE 1-6	F LE 1-6
	WAC EN-12150-R-AR	F L 1	F L 1	F L 1	✓	F L 1	F LE 1-6	Dim 35% 1-6	✓	4 M L	5 M L
	Solutions NET-1075	+	+	+	+	+	F LE 1-6	Dim 35% 1-6	SH LE 1	✓	✓
	LIF LF050C						F LE 1-6	Dim 35% 1-6	F LE 1-6	✓	✓
	Elco ET526	✓	✓	✓	minor F LE	✓	F LE	minor F LE	F LE	+	✓
	Juno T537	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	Juno R701	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	Juno R731	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	Nora NTL-207	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	Nora NTLE-207	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	WAC-CI HHT-802	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	WAC-CI HHT-809	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	WAC-CI HHT-826	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	WAC-CI HHT-856	✓	✓	✓	✓	✓	F LE	Dim 35%	✓	✓	✓
	WAC W-070	+ -	+ -	+ -	+ -	+ -	F LE	+	+	+	+
	WAC HHT-802	NC	NC	NC	NC	NC	NC	NC	NC	NC	NC

Overall Rating	
✓	Dims Down ≤ 20% (no flickering, no audible noise, wide dimming range)
+	Min 2 lamps: Dims Down ≤ 20% (minimal adjustment may be required, dead travel exists, minor audible noise)
+ -	Min 3 lamps: Dims Down ≤ 20% (flickering observed, steppy dimming appears, voltage reverse, audible noise may be present)
NC	Not Compatible (major flickering observed, audible noise, no dimming range, does not turn off)