

## Dimmer Compatibility Guide

Product Family Name: Item Number: Ordering Code: Item Number: Ordering Code: 776926 LED9A19/40/FIL/3

			Lamps per Dimmer				
	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
		IllumaTech	IPI06	Best	1	6	Dims down to 1%
	Leviton	SureSlide	6633-P	Best	1	6	Dims down to 1%
<u>_</u>		Vizia	VPI06-1LZ	Best	1	6	Dims down to 1%
		Toggler	TG-600	Best	1	6	Dims down to 1%
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Lutron	Lumea	LGCL-600	Best	1	6	Dims down to 1%
		Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Good	3	6	Dims down to 1%
	Legrand	Titan	CD703-PW	Good	3	6	Dims down to 1%
		Harmony	D703-PTC	Good	3	6	Dims down to 1%
		Harmony	H703-PTC	Good	3	6	Dims down to 1%
<u>.</u>			-				
<b>CFL/LED</b>	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Sunnata	STCL - 153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
<u>_</u>		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
	Legrand	Radiant	RHCL453PW	Best	1	6	Dims down to 1%
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
		IllumaTech	IPE04	Best	1	6	Dims down to 1%
		Decora	6615-P	Not compatible	1	6	Dims down to 50%
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%
		Diva	DVELV-300P	Best	1	6	Dims down to 1%
		Maestro	MAELV-600	Best	1	6	Dims down to 1%
		Skylark	SELVB-300P	Best	1	6	Dims down to 1%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
					1		Doesn't turn off with 1-5
	Legrand	Scene Director	SCELV	Not compatible	1	6	Doesn't turn off with 1-5
						_	
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Best	1	6	Dims down to 1%
		Decora	6613-P	Best	1	6	Dims down to 1%
	Lutron	Maestro	MALV-600	Not compatible	1	6	Doesn't torn on with 1-6
		Harmony	DLV703-PW	Best	1	6	Dims down to 1%
	Legrand	Titan	CDLV703-PW	Good	2	6	Dims down to 1%
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 1%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 1%
	Deako	Single pole Smart dimmer	DS-CD1M-WHMC-UCV	Good	1	6	Dims down to 20%
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%
		1=*			-		123 401111 to 1/3
Universal	Legrand	Adorne SofTap	ADTP703TU	Good	2	6	Dims down to 25%
		Miro Decorator	DRD4-W	Good	4	6	Dims down to 25%
					2		
		Harmony	H703PTUTC	Good		6	dims down to 25%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
	C	Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 1%
	Cooper	Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating						
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.					
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.					
	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) i moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.					
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.					
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.					
Low End (L.E.) Dead Travel	bettermines now mount, if any, dead travel exists at the top and bottom of the diminer's range. Dead travel is when the shufer can be moved without an exting the light level.					

Contact Information:
Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com 2024 Bulbrite Industries Inc. Il Rights Reserved.