



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: A-Type Dimmable: A19, A21
Item Number: 774009
Ordering Code: LED9A19/827/D/2

Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
				Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Good	1	6	Minor flicker at 10% with 1 and at 2% with 4-6, dims down to 1%
		SureSlide	6633-P	Good	1	6	Minor flicker at 1% with 4, dims down to 1%
		Vizia	VPI06-1LZ	Good	2	6	Dms down to 1% with 2-6
	Lutron	Toggle	TG-600	Good	1	6	Minor flicker at 10% with 3-6, dims down to 1%
		Diva	DV-600	Good	1	6	Minor flicker at 10% & 50% with 1, minor flicker at 5% with 2-6, dims down to 1%
		SkyLark	S-600	Good	1	6	Minor flicker at 5% with 3-6
		Maestro	MAW-600	Good	3	6	Dms down to 5% with 1-6
	Legrand	Titan	CD703-PW	Good	1	6	Minor flicker at LE with 1-4, dims down to 1%
		Harmony	D703-PTC	Good	1	6	Minor flicker at 1% with 1, dims down to 1%
		Harmony	H703-PTC	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 1% with 1-6
		Sureslide	6674	Best	1	6	Dims down to 1% with 1-6
		Decora	6672	Best	1	6	Dims down to 1% with 1-6
	Lutron	SkyLark Countour	CTCL-153	Best	1	6	Dims down to 1% with 1-6
		Diva	DVCL-153PL	Best	1	6	Dims down to 1% with 1-6
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1% with 1-6
		SkyLark	SCL-153P	Best	1	6	Dims down to 1% with 1-6
		Toggle	TGCL-153PH	Best	1	6	Dims down to 1% with 1-6
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1% with 1-6
		Harmony	CDL453-PTC	Good	1	6	Minor flicker at Med with 2, dims down to 1%
	Legrand	Harmony	HCL453PTC	Good	1	6	Minor flicker at Med with 1, dims down to 1%
		Adorne Paddle	ADPD453LM2	Bad	1	6	Minor flicker at Med with 1, flicker at HE with 2-6, dims down to 10%
	Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6
IlumaTech			JPE04	Good	1	6	Minor flicker at Med with 1-6, dims down to 1%
Decora			6615-P	Good	1	6	Minor flicker at Med with 1-6, dims down to 1%
Lutron		SkyLark Countour	CTELV-303P	Good	1	6	Minor flicker at Med with 1-6, dims down to 1%
		Diva	DVELV-300P	Good	1	6	Minor flicker at Med with 1-6, dims down to 1%
		Maestro	MAELV-600	Good	1	6	Minor flicker at Med with 2-6, dims down to 1%
		SkyLark	SELVB-300P	Good	1	6	Minor flicker at Med with 2-6, dims down to 1%
Legrand		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1% with 1-6
		Scene Director	SCELV	Best	1	6	Dims down to 1% with 1-6
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 1% with 2-6
		Decora	6613-P	Good	1	6	Minor flicker at 5% & 1% with 1, minor flicker at 50% with 3-6, dims down to 1%
	Lutron	Maestro	MALV-600	Not Compatable	1	6	It does not turn on with 1-6
		Harmony	DLV703-PW	Good	1	6	Minor flicker at 1% with 1-6, dims down to 1%
	Legrand	Titan	CDLV703-PW	Good	1	6	Minor flicker at 1% with 1-6, dims down to 1%
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 10% with 1-6
	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ	N/A			
	Insteon	SwitchLin Remote Control dimmer		N/A			
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Minor flicker 1% - 10% with 1-6, dims down to 1%
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A			
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 5% with 1-6
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 1% with 1-6
		Miro Decorator	DRD4-W	Good	1	6	Minor flicker at 5% with 1-6, dims down to 1%
		Harmony	H703PTUTC	Best	1	6	Dims down to 1% with 1-6
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1% with 1-6
		Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 1% with 1-6
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at 20% with 1, dims down to 4%
		Skye	SAL06P-W-K-L	Good	1	6	Minor flicker at 5% with 1, dims down to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor flicker at 10% with 1 and at 2% with 4-6, dims down to 1%
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact Information:
Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2017 Bulbrite Industries Inc.
All Rights Reserved.