



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: LED A-Type Dimmable
Item Number: 774008
Ordering Code: LED9A19/840/D/2-C

Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
				Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
		SureSlide	6633-P	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
		Vizia	VPI06-1LZ	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 4%
	Lutron	Toggle	TG-600	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
		Diva	DV-600	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
		Skylark	S-600	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
	Legrand	Maestro	MAW-600	Good	3	6	Minor flicker at LE below 10% with 3-6, dims down to 3%
		Titan	CD703-PW	Bad	1	6	Flicker at 5%-30% & 80% with 1, flicker LE -Med with 2, dims down to 5%
		Harmony	D703-PTC	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
	Harmony	H703-PTC	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%	
CFU/LED	Leviton	IlumaTech	IPL06	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
		Sureslide	6674	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
		Decora	6672	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 2%
	Lutron	Skylark Countour	CTCL-153	Best	1	6	Need to adjust the dial to change the lowest dimmer light level to 10% to obtain no flicker
		Diva	DVCL-153PL	Best	1	6	Need to adjust the dial to change the lowest dimmer light level to 10% to obtain no flicker
		Maestro	MAEL-153MLH	Best	1	6	Need to adjust the dial to change the lowest dimmer light level to 10% to obtain no flicker
	Legrand	Skylark	SCL-153P	Best	1	6	Need to adjust the dial to change the lowest dimmer light level to 10% to obtain no flicker
		Toggle	TGCL-153PH	Best	1	6	Need to adjust the dial to change the lowest dimmer light level to 10% to obtain no flicker
		Radio RA	RA2RR-6CL-PD	Best	1	6	Need to adjust the dial to change the lowest dimmer light level to 10% to obtain no flicker
		Harmony	DCL453-PTC	Best	1	6	Need to adjust the dial to change the lowest dimmer light level to 10% to obtain no flicker
		Harmony	HCL453PTC	Best	1	6	Need to adjust the dial to change the lowest dimmer light level to 10% to obtain no flicker
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 10% with 1-6
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Minor flicker at LE with 1-6, dims down to 4%
		IlumaTech	JPED4	Good	1	6	Flicker at Med with 2, minor flicker at Med with 1-6, dims down to 1%
		Decora	6615-P	Good	1	6	Minor flicker at Med with 1-6, dims down to 20%
	Lutron	Skylark Countour	CTELV-303P	Good	1	6	Minor flicker at Med with 1, dims down to 5%
		Diva	DVELV-300P	Good	1	6	Minor flicker at Med with 1, dims down to 5%
		Maestro	MAELV-600	Good	1	6	Minor flicker at Med with 1, dims down to 5%
	Legrand	Skylark	SELVB-300P	Good	1	6	Minor flicker at Med with 1, dims down to 5%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 5%
		Scene Director	SCELV	Good	1	6	Minor flicker at LE at 5% with 1-6, dims down to 5%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%
		Decora	6613-P	Good	1	6	Minor flicker at Med with 1, minor flicker at LE with 1-6, dims down to 1%
	Lutron	Maestro	MALV-600	Good	3	6	Minor flicker at LE with 3-6, dims down to 3%
		Harmony	DLV703-PW	Good	1	6	Minor flicker at Med with 1, minor flicker at LE with 1-6, dims down to 1%
	Legrand	Titan	DLV703-PW	Bad	1	6	Flicker at med with 1-2, minor flicker at LE with 3-6, dims down to 1%
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Minor flicker at LE from 1%-10% with 1-6, dims down to 1%
	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ	N/A			
	Insteon	SwitchLin Remote Control dimmer		N/A			
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Minor flicker at LE from 1%-10% with 1-6, dims down to 1%
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A			
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
	GE	Z WAVE	ZW3005		1	6	Minor flicker at LE from 5%-10% with 1-6, dims down to 5%
Universal	Legrand	Adorne SofTap	ADTP703TU	Good	1	6	Minor flicker 2%-20% with 1-6, dims down to 2%
		Miro Decorator	DRD4-W	Good	1	6	Minor flicker at LE below 10% with 1-6, dims down to 1%
		Harmony	H703PTUC	Good	1	6	Minor flicker 2%-20% with 1-6, dims down to 2%
		Adorne Whisper	ADWR700MMTUW2	Good	1	6	Minor flicker at LE 1%-10% with 1-6, dims down to 1%
	Cooper	Adorne Touch	ADTH700MMTUW2	Good	1	6	Minor flicker at LE 1%-10% with 1-6, dims down to 1%
		Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at LE 1%-20% with 1-6, dims down to 1%
		Skye	SAL06P-W-K-L	Good	1	6	Minor flicker at LE 1%-20% with 1-6, dims down to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor aud
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact Information:

Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2017 Bulbrite Industries Inc.
All Rights Reserved.